

TEST-I Multi Function PC Cable Tester



TEST-I tests and analyzes a comprehensive range of PC connector types and the most commonly used flat cables.

TEST-I tests each pin connection to identify open wires, short wires, cross wires and miss-wires, miss-wires. It also shows pin-to-pin connectivity and also records up to a 100 test results. Data collected is saved and uploaded to PC via USB for analysis. It has an integrated LCD display (with back light function), user clearly determines the cable Pin wiring easily and efficiently. TEST-I makes an excellent and essential tool for a system integrator to quickly troubleshoot and perform pin to pin test on PC cables.

FEATURES

- Identify open wires, short wires, cross wires and miss-wires connectivity
- Support 18 flat types of PC connectors
- 100 test results are saved and transferred to PC via USB line
- Alphanumeric LCD display with back light
- Low battery indicator
- Handheld

SPECIFICATIONS

Connectors	:	IDC40, IDC34, DVI29, HDBI15M/F3 DB9M/F, COAX, BNC, RJ11, RJ45 1394-6P, 1394-P, SATA, USB (A/B), HDMI, RCA
Control Switch	:	Power, Up Down, Delete, Save, Cancel, and Enter
Display	:	LCD type with back light 2 rows-16 characters
Memory	:	18 test results
PC Interface	:	USB Port
Software	:	To save and edit test data
Power	:	DC 9V battery /Compartment DC 9V, 150mA power jack
Emission	:	CE, RoHS compliant
ACCESSORIES	:	Batteries, Instruction Manual

FALCON ELECTRO - TEK PVT. LTD.

Hema Industrial Estate, Near Meghwadi Police Station, Sarvoday Nagar, Jogeshwari (East), Mumbai - 400 060. INDIA.
Tel: +91-22-28348429 / 28248665 / 28346339 / 28343608 Fax: +91-22-28370165.
Email: falcon@falconindia.biz Website: www.falconindia.biz