
## THREE PHASE DIGITAL VOLTMETER



- Bright LED 7 Segment 14.2 mm Display.
- Microcontroller based...
- Measure Phase Neutral Voltages, also Phase to Phase Voltages.
- Auto Scroll Facility Available...
- Accuracy Clas: 1.0.
- Comact Standard DIN Flush Mounting.
- ⇒ Size : 96mm x 96 mm x 75mm.

## THREE PHASE DIGITAL AMMETER



- Bright LED 7 Segment 14.2 mm Display.
- Microcontroller based.
- Auto Scroll Facility Available.
- Available range : 30.0/5A to 1500/5A.
- C.T. Ratio selectable by DIP Switch at rear..
- Accuracy Clas: 1.0.
- Comact Standard DIN Flush Mounting.
- Size : 96mm x 96 mm x 75mm.

## **DIGITAL EARTH RESISTANCE TESTER**

Electronic Digital Earth Resistance Tester is direct replacement of the conventional hand generator type.

## Features:

Earth

Resistance Range : 0-10/100/1000 (ERT - 1501)

0-20/200/2000 (ERT-1501)

Display : Large Backlight LCD with dual display

Multimeter

Function Range : 200 kOhms, 750V/ACV, 1000V/DC.

Sampling Rate : 2.5 times per second.

Zero Adjustment : Automatic

Power Source : DC9V (6x1.5 V Size "A A" battery
Dimensions : 200(L) x 92 (W) x 50 (H) mm
Weight : Approx 700g include battery

Accessories : 4 sets Test Kits, 4pcs iron rods, 6pcs battery,

Hard Carrying Case, manual.

Optional

Accessories : Re - chargeable Battery and battery charger.



